

## 2.2 Suitable ferrules and retrofit kits

With the FC-2#0, you can either:

- strip conductors automatically or
- strip conductors automatically and crimp with ferrules.

Flexible conductors of class 2, 5, and 6 standard according to DIN VDE 0295 and ferrules as loose products according to DIN 46228-4 are processed.

The following loose ferrules can be processed with the FC-2#0:









Table 2-2 Suitable ferrules

Basic device	Cross-section mm <sup>2</sup>	Sleeve length mm	DIN color range	Comment	Order No.
FC-200	0.25/0.34	6	yellow/	FC-2#0-TOOLKIT 0,34/ 6-8	included in FC-200
	0.25/0.34	8	turquoise		
	0.50	6	white		
	0.50	8			
	0.50	10			
	0.50	12			
	0.75	6	gray		
	0.75	8			
	0.75	10			
	0.75	12			
	1.00	6	red		
	1.00	8			
	1.00	10			
	1.00	12			
1.50	6	black			
1.50	8				
1.50	10				
1.50	12				
2.50	8	blue	FC-2#0-TOOLKIT 2,5	006645	
	10				
	12				
	4.00	10	gray	FC-2#0-TOOLKIT 4,0/10	006650
FC-250	4.00	10	gray	FC-250-TOOLKIT 4/10-12	006630
		12			
	6.00	12	yellow	FC-250-TOOLKIT 6-12	006813
	10.00	12	red	FC-250-TOOLKIT 10-12	006814

The FC-2#0 retrofit kit...-TOOLKIT.... is a case that contains

- Feeder bowl
- Reversing base sleeve

### A3 Spare parts

Part	Cross section	Order No.	FC-200	FC-250
Feeder bowl 	0,25 - 0,34 mm <sup>2</sup> 0,5 - 1,5 mm <sup>2</sup> 2,5 mm <sup>2</sup> 4 mm <sup>2</sup> (2,5 mm <sup>2</sup> GB) 6 mm <sup>2</sup> 10 mm <sup>2</sup>	FC2-006602 FC2-006601 FC2-008989 FC2-006603 FC2-006651 FC2-006652	X X X X	X X X
Separation plate 	0,25/0,34 mm <sup>2</sup> 0,5 - 1,5 mm <sup>2</sup> 2,5 mm <sup>2</sup> 4 mm <sup>2</sup> 6 mm <sup>2</sup> 10 mm <sup>2</sup>	FC2-006653 FC2-006654 FC2-006655 FC2-006656 FC2-006657 FC2-006658	X X X X	X X X
Reversing base sleeve 	0,25/0,34 mm <sup>2</sup> 0,5 - 1,5 mm <sup>2</sup> 2,5/4 mm <sup>2</sup> 6 mm <sup>2</sup> 10 mm <sup>2</sup>	FC2-004755 FC2-004666 FC2-004758 FC2-004757 FC2-004759	X X X	X X X
Sleeve receiver 	0,14 mm <sup>2</sup> 0,25/0,34 mm <sup>2</sup> 0,5 mm <sup>2</sup> 0,75 mm <sup>2</sup> 1 mm <sup>2</sup> 1,5 mm <sup>2</sup> 2,5 mm <sup>2</sup> 4 mm <sup>2</sup> 4 mm <sup>2</sup> 6 mm <sup>2</sup> 10 mm <sup>2</sup>	FC2-006649 FC2-006597 FC2-006389 FC2-006390 FC2-006391 FC2-006392 FC2-006393 FC2-006598 FC2-006513 FC2-006514 FC2-006515	X X X X X X X X	X X X
Cord-centering funnel 	0,25/0,34 mm <sup>2</sup> 0,5 - 1,5 mm <sup>2</sup> 2,5 mm <sup>2</sup> 4 mm <sup>2</sup> 6 mm <sup>2</sup> 10 mm <sup>2</sup>	FC2-006604 FC2-006521 FC2-006605 FC2-006522 FC2-006659 FC2-006660	X X X X	X X X
Stripping blade 	0,25 - 2,5 mm <sup>2</sup> 4 mm <sup>2</sup> 6 mm <sup>2</sup> 10 mm <sup>2</sup>	FC2-006642 FC2-003371 FC2-003841 FC2-003842	X X	X X X
Crimping jaws 	0,25-0,34 mm <sup>2</sup> -8 0,5-2,5 mm <sup>2</sup> - 12 4 mm <sup>2</sup> - 10 mm 4 mm <sup>2</sup> - 12 mm 6 mm <sup>2</sup> - 12 mm 10 mm <sup>2</sup> - 12 mm	FC2-006506 FC2-006504 FC2-004764 FC2-006661 FC2-006662 FC2-006663	X X X	X X X
Mains fuse 	T2A/250V 5 x 20 mm	FC2-004177	X	X

OK

OK

OK

OK

OK

OK

OK